

## MVE136 Random Signals Analysis – Test Exam

AIDS: Beta or 2 sheets (4 pages) of hand-written notes (computer print-outs and/or xerox-copies are not allowed), but not both these aids.

GRADES: 12 (40%), 18 (60%) and 24 (80%) points for grade 3, 4 and 5, respectively.

GOOD LUCK!

**Task 1.** Let  $(X, Y)$  be a continuous random variable with PDF  $f_{X,Y}(x, y) = e^{-x-y-xy} / (\int_0^\infty (1+z)^{-1} e^{-z} dz)$  for  $x, y \geq 0$  (and 0 otherwise). Find  $\mathbf{E}\{X|Y=y\}$ . **(5 points)**

**Task 2.** Find the probability  $Pr(X(1)+X(2)+X(3) > 6)$  for a continuous time WSS Gaussian process  $X(t)$  with mean  $\mu_X = 1$  and autocorrelation function  $R_{XX}(\tau) = e^{-|\tau|} + 1$  for  $\tau \in \mathbb{R}$ . **(5 points)**

**Task 3.** Consider a discrete time Markov chain  $X(n)$  with state space  $E$  and transition probability matrix  $P$  given by

$$E = \{0, 1\} \quad \text{and} \quad P = \begin{bmatrix} 1/2 & 1/2 \\ 1/4 & 3/4 \end{bmatrix},$$

respectively. What initial distribution  $\pi(0)$  of the chain will give a distribution  $\pi(2)$  of the value of the chain  $X(2)$  at time  $n = 2$  given by  $\pi(2) = [1/3 \ 2/3]$ ? **(5 points)**

**Task 4.** The PSD  $S_{XX}(f)$  of a continuous time WSS process  $X(t)$  has the properties to be real and symmetric (=even). Prove one of these properties. **(5 points)**

**Task 5.** A WSS discrete-time random process  $X(n)$  with PSD  $S_{XX}(f)$  is input to two different LTI systems with transfer functions  $H_1(f)$  and  $H_2(f)$ , respectively. Find the cross spectral density  $S_{Y_1 Y_2}(f)$  between the outputs  $Y_1(n)$  and  $Y_2(n)$  from the two LTI systems. **(5 points)**

**Task 6.** Compute the autocorrelation function  $r_x[n]$  for  $n = 0$  and  $n = 1$  when  $x[n]$  is an AR(1)-process with parameter  $a_1 = 0.7$ . You can assume that the input noise has variance  $\sigma_e^2 = 1$ . **(5 points)**